



DVI Booster

USER MANUAL

www.gefen.com

ASKING FOR ASSISTANCE

Technical Support:

Telephone (818) 884-6294
(800) 545-6900
Fax (818) 884-3108

Technical Support Hours:

9:00 AM to 5:00 PM Monday thru Friday.

Write To:

Gefen Inc.
C/O Customer Service
6265 Variel Ave.
Woodland Hills, CA 91367-9897

Notice

Gefen Inc. reserves the right to make changes in the hardware, packaging and any accompanying documentation without prior written notice.

DVI Booster is a trademark of Gefen Inc.

© 2006 Gefen Inc., All Rights Reserved

TABLE OF CONTENTS

- 1 Introduction
- 2 Features
- 3 Panel Descriptions
- 4 Connecting and Operating the DVI Booster
- 5 Specifications
- 6 Warranty

INTRODUCTION

Congratulations on your purchase of the ex•tend•it DVI Booster. Your complete satisfaction is very important to us. Gefen's line of KVM (Keyboard Video & Mouse), DVI, ADC, USB, switches, extenders, converters and hubs is designed to make computer use more comfortable, more productive and less expensive. KVM switches allow access to multiple computers from a single keyboard, while the extenders give the user control over a computer up to 330 feet away from the work area. The ex•tend•it line offers solutions for noise, space and security concerns, data center control, information distribution, conference room presentation, and school and corporate training environments.

Our Commitment

Gefen will always offer the finest quality product at the best possible price. Included in that price is a lifetime of free support from a team of outstanding engineers.

Introduction

The ex•tend•it DVI Booster extends the length of any DVI cable by regenerating the DVI signal before it outputs to the DVI monitor or projector. The DVI Booster will clean out the digital noise (sparkles) in your picture. The ex•tend•it DVI Booster is connected with a DVI (male to male) cable from the computer DVI graphic port to the DVI Booster input. The DVI Booster output uses a second DVI (male to male) cable to go from the output to any DVI display or projector with a DVI connector. The box is placed near the display to remove any noise that has been generated by a long DVI cable.

FEATURES

Features

- Connects DVI computers with DVI outputs to DVI compatible displays or projectors
- Maintains highest DVI single link video resolution
- Supports DDWG standard for DVI compliant monitors
- Installs in minutes

Includes:

DVI Booster

User's Manual

PANEL DESCRIPTIONS



Connecting and Operating the DVI Booster

How to Connect the DVI Booster

- 1- Connect the long DVI cable from the source into the “DVI In” on the front of the DVI Booster. The DVI Booster is placed next to your display to regenerate the DVI cable.
- 2- Connect a short DVI cable from the “DVI Out” connection in the back of the DVI Booster to your display or projector.
- 3- If there is no video signal or there is signal noise in the picture, adjust the EQ trimpod located underneath the DVI Booster using a small flat head screw driver.

SPECIFICATIONS

Video Amplifier Bandwidth	1.65 Gbps
Video Pixel Rate	165 Mhz
Input Video Signal	1.2 volts p-p
Input DDC Signal	5 volts p-p (TTL)
Maximum Single Link Range	1920 x 1200 x 60hz
DVI Input/Output Connector Type	DVI-I 29 pin female (digital only)
Dimensions	1.75" W x 1" H x 2.25" D
Shipping Weight	1 lb.

WARRANTY

Gefen Inc. warrants the equipment it manufactures to be free from defects in material and workmanship.

If equipment fails because of such defects and Gefen Inc. is notified within one (1) year from the date of shipment, Gefen Inc. will, at its option, repair or replace the equipment, provided that the equipment has not been subjected to mechanical, electrical, or other abuse or modifications.

Equipment that fails under conditions other than those covered will be repaired at the current price of parts and labor in effect at the of repair. Such repairs are warranted for ninety (90) days from the day of reshipment to the Buyer.

This warranty is in lieu of all other warranties expressed or implied, including without limitation, any implied warranty or merchantability or fitness for any particular purpose, all of which are expressly disclaimed.

The information in this manual has been carefully checked and is believed to be accurate. However, Gefen Inc. assumes no responsibility for any inaccuracies that may be contained in this manual. In no event will Gefen Inc., be liable for direct, indirect, special, incidental, or consequential damages resulting from any defect or omission in this manual, even if advised of the possibility of such damages. The technical information contained herein regarding DVI Booster features and specifications is subject to change without notice.

* MA- DVI - 141b*

6265 Variel Avenue Woodland Hills, CA 91367
1-800-545-6900 818-884-6294 fax: 818-884-3108
www.gefen.com gsinfo@gefen.com