



PU-607BD-RX

HDMI over Single CAT5e/6/7 HDBaseT™ - Bi-Directional
PoE Receiver (Full 5Play™ & Single LAN up to 100m)

OPERATION MANUAL

DISCLAIMERS

The information in this manual has been carefully checked and is believed to be accurate. CYP (UK) Ltd assumes no responsibility for any infringements of patents or other rights of third parties which may result from its use.

CYP (UK) Ltd assumes no responsibility for any inaccuracies that may be contained in this document. CYP (UK) Ltd also makes no commitment to update or to keep current the information contained in this document.

CYP (UK) Ltd reserves the right to make improvements to this document and/or product at any time and without notice.

COPYRIGHT NOTICE

No part of this document may be reproduced, transmitted, transcribed, stored in a retrieval system, or any of its part translated into any language or computer file, in any form or by any means—electronic, mechanical, magnetic, optical, chemical, manual, or otherwise—without express written permission and consent from CYP (UK) Ltd.

© Copyright 2011 by CYP (UK) Ltd.

All Rights Reserved.

Version 1.1 August 2011

TRADEMARK ACKNOWLEDGMENTS

All products or service names mentioned in this document may be trademarks of the companies with which they are associated.

SAFETY PRECAUTIONS

Please read all instructions before attempting to unpack, install or operate this equipment and before connecting the power supply.

Please keep the following in mind as you unpack and install this equipment:

- Always follow basic safety precautions to reduce the risk of fire, electrical shock and injury to persons.
- To prevent fire or shock hazard, do not expose the unit to rain, moisture or install this product near water.
- Never spill liquid of any kind on or into this product.
- Never push an object of any kind into this product through any openings or empty slots in the unit, as you may damage parts inside the unit.
- Do not attach the power supply cabling to building surfaces.
- Use only the supplied power supply unit (PSU). Do not use the PSU if it is damaged.
- Do not allow anything to rest on the power cabling or allow any weight to be placed upon it or any person walk on it.
- To protect the unit from overheating, do not block any vents or openings in the unit housing that provide ventilation and allow for sufficient space for air to circulate around the unit.

REVISION HISTORY

VERSION NO.	DATE	SUMMARY OF CHANGE
v1.00	11/02/2014	First release

CONTENTS

1. Introduction	6
2. Applications	6
3. Package Contents	6
4. System Requirements	6
5. Features.....	7
6. Operation Controls and Functions	8
6.1 Receiver Front and Rear Panels	8
6.2 IR Cable Pin Assignment	9
6.3 D-Sub 9 Pin Definitions	9
7. Connection Diagram	10
8. Specifications.....	11
9. Acronyms.....	12

1. INTRODUCTION

The PU-607BD-RX Receiver allows uncompressed HDMI signals and IP data to be received via a Single CAT5e/6/7 cable. This solution has the added features of RS-232 and 2-way IR control functionality over the same CAT5e/6/7 cable. These combined HDMI and control signals can be transmitted up to lengths of 100 metres. This Receiver is designed to be used with the PU-607BD-TX or PU-607BDWP-TX Transmitters only, which enables Bi-Directional Power over Ethernet (PoE) functionality.

2. APPLICATIONS

- /// Household entertainment sharing and control
- /// Lecture room display and control
- /// Showroom display and control
- /// Meeting room presentation and control
- /// Classroom display and control

3. PACKAGE CONTENTS

- /// 1×PU-607BD-RX Receiver
- /// 1×IR Blaster
- /// 1×IR Receiver
- /// 1×24V/1.25 A DC Power Adaptor
- /// Operation Manual

4. SYSTEM REQUIREMENTS


Input HDMI source equipment such as DVD/Blu-ray player and HDMI equipped output display (TV or monitor).

5. FEATURES

- /// Supports all v1.4 HDMI resolutions including 4K.
 - /// Supports uncompressed video/audio up to 10.2Gbps
 - /// Common supported resolutions: HDTV: 480p, 576p, 720p, 1080i, 1080p, 1080p24; PC: VGA, SVGA, XGA, WXGA, SXGA, UXGA, WUXGA.
 - /// HDMI, HDCP, & DVI compliant
 - /// Supports HDCP repeating and CEC functions
 - /// Uncompressed data transfer over single CAT cable (100m - CAT6/7; 80m - CAT5e)
 - /// Uncompressed video 1080p, 60Hz, 48bits
 - /// Audio support up to 7.1CH & Dolby TrueHD, DTS-HD
 - /// 5Play™ convergence: HDMI, LAN, Bi-Directional POE & Control (IR & RS232)
 - /// Supports 3D signals
 - /// Supports Bi-Directional Power over Ethernet (PoE)
- Note: Only compatible with PU-607BD-TX & PU-607BDWP-TX Transmitters*



6. OPERATION CONTROLS AND FUNCTIONS

6.1 Receiver Front and Rear Panels



- 1 **HDMI Out:** Connect to a HDMI equipped TV/monitor for display of the HDMI input source signal.
- 2 **LAN:** Connect to a PC or Laptop to the Internet or network connection.
- 3 **RS-232 Out:** Connect to the device that is to be controlled (via D-Sub 9 pin female cable) by RS-232 commands.
- 4 **Power LED:** This blue LED will illuminate when the device is connected to a power supply.
- 5 **DC 24V:** Plug the 24 V DC power supply into the unit and connect the adaptor to an AC outlet. Only one side of power needs to be connected to activate both transmitter and receiver.
- 6 **IR 2 Blaster:** Connect to the supplied IR blaster cable for IR signal transmission. Place the IR blaster in direct line of sight of the equipment to be controlled.
- 7 **IR 1 Extender:** Connect to the supplied IR receiver cables for IR signal reception. Ensure that remote being used is within the direct line-of-sight of the IR extender.
- 8 **Link LED:** The yellow LED will illuminate when both the input and output signals are connected.
- 9 **CAT5e/6 In:** Connect to the transmitter unit with a Single CAT5e/6 cable for transmission of all data signals.


6.2 IR Cable Pin Assignment



6.3 D-Sub 9 Pin Definitions

Pin	Define TX / RX
1	N/C
2	TxD / RxD
3	RxD / TxD
4	N/C
5	GND
6	N/C
7	N/C
8	N/C
9	N/C

7. CONNECTION DIAGRAM



Note: Only one of the units need to be connected to power, either the transmitter or receiver, in order for both to operate. In this example the transmitter is powering the receiver

8. SPECIFICATIONS

Video Bandwidth	300MHz / 9Gbps
Ethernet Speed	100 Mbps
Receiver	
Input	1×CAT5e/6, 1×IR Extender
Output	1×HDMI, 1×RS-232, 1× IR Blaster, 1× LAN
HDMI In/Out Cable Distance	Up to 10 Meters
CAT6 In/Out Cable Distance	Up to 100 Meters
HDMI In/Out Supports Resolution	480i~1080p@50/60, 1080p@24, VGA~WUXGA
IR Frequency	30~50 kHz
ESD Protection	Human Body Model: ±8kV (air-gap discharge) ±4kV (contact discharge)
Power Supply	24V/1.25A DC (US/EU Standards, CE/FCC/UL certified)
Dimensions	102mm (W)×113mm (D)×25mm (H)/each
Weight	252g (TX), 256g (RX)
Chassis Material	Aluminum
Silkscreen Color	Silver
Power Consumption	13 W
Operating Temperature	0 °C~40 °C/32 °F ~104 °F
Storage Temperature	-20 °C~60 °C/-4 °F~140 °F
Relative Humidity	20~90% RH (non-condensing)

9. ACRONYMS

ACRONYM	COMPLETE TERM
CAT5e	Category 5 Cable
CAT6	Category 6 Cable
CEC	Consumer Electronics Control
DVI	Digital Visual Interface
HDCP	High-bandwidth Digital Content Protection
HDMI	High Definition Multimedia Interface
IR	Infrared



CYP (UK) Ltd., Unit 7, Shepperton Business Park, Govett Avenue, Shepperton,
Middlesex, TW17 8BA

Tel: +44 (0) 20 3137 9180 | Fax: +44 (0) 20 3137 6279

Email: sales@cypeurope.com

www.cypeurope.com

v1.00